


OpenGear Converter SDI to Audio



Includes everything you need to de-embed 4 channels of analog audio or 8 channels of AES/EBU digital audio from any SDI video connection. Easily access the audio in any SDI video connection for output to audio equipment such as audio mixers, analog broadcast decks, audio monitors and more!

\$495

Connections

SDI Video Input

Switchable between SD, HD and Level B 3G-SDI.

SDI Video Output

Automatically matches the SD, HD and 3G-SDI video input.

Analog Audio

4 channels of professional balanced digital with openGear™ standard 3 pin connections.

AES/EBU Digital Audio

8 channels of professional balanced digital with openGear™ standard 3 pin connections.

SDI Redundant Input

Automatically switches over if main SDI input is lost.

Multi Rate Support

Auto detection of SD, HD and Level B 3G-SDI inputs.

Updates and Configuration

Via USB 2.0 high speed. (480 Mb/s)

Reclocking

Yes



Standards

SD Format Support

525i59.94 NTSC, 625i50 PAL

HD Format Support

720p50, 720p59.94, 720p60
 1080p23.98, 1080p24, 1080p25,
 1080p29.97, 1080p30, 1080p50,
 1080p59.94, 1080p60
 1080PsF23.98, 1080PsF24, 1080PsF25,
 1080PsF29.97, 1080PsF30
 1080i50, 1080i59.94, 1080i60

SDI Compliance

SMPTE 292M, SMPTE 259M,
 SMPTE 296M, ITU-R BT.656 and
 ITU-R BT.601.

SDI Video Rates

SDI video connections are switchable between standard definition and high definition.

SDI Audio Sampling

Television standard sample rate of 48 kHz and 24-bit.

SDI Color Precision

4:2:2

SDI Color Space

YUV

2K Format Support

1080p29.98, 1080p24, 1080p25
1080PsF23.98, 1080PsF24, 1080PsF25

SDI Video Sampling

4:2:2

SDI Auto Switching

Automatically selects between SD SDI, HD-SDI and 3G-SDI.

Software

Software Control

Mac OS X™ and Windows™ software upgrade via USB.

Internal Software Upgrade

Via included updater application.

Operating Systems



macOS 10.12 Sierra,
macOS High Sierra
10.13 or later.




Windows 8.1 or
Windows 10.

Settings Control

OpenGear DashBoard network control software, Mini Switches or USB software.

Physical Specifications



Environmental Specifications

Operating Temperature

0° to 40° C (32° to 104° F)

Storage Temperature

-20° to 45° C (-4° to 113° F)

Relative Humidity

0% to 90% non-condensing

What's Included

OpenGear Converter SDI to Audio.
SD card with software and manual.
Double width rear connector.

Warranty

3 Year Limited Manufacturer's Warranty.

All items on this website are copyright Blackmagic Design Pty. Ltd. 2018, all rights reserved.
All trademarks are property of their respective owners. MSRP excludes sales taxes/duties and shipping costs.
This website uses remarketing services to advertise on third party websites to previous visitors to our site.
You can opt out at any time by changing cookie settings. [Privacy Policy](#)

Blackmagic Design Authorized Reseller